

# LUCKY EVO B

1002D9.02 + 1002A3.99

LUCKY EVO B: HF D/I 120W L2811 4KNE PUSH + LUCKY EVO B: DIFF. OPALE PER L2811

**novalux**  
ITALIAN LIGHTING DESIGN SINCE 1948



## Features

Use: Indoor  
Type of installation: SUSPENDED  
Emission: DIRECT/INDIRECT  
Optics: OPAL  
Colour: BLACK  
Dimming: PUSH  
Emergency: NO  
L: 2811mm  
A: 52mm  
H: 91mm  
Made in: ITALY  
Warranty: 5 years  
Weight: 9.4kg

## Tech data

Luminaire input power: 132.7W  
Luminaire luminous flux: 11723lm  
Indirect luminous flux: 6678lm  
IP: 40  
Insulation class: I  
Supply voltage: 220-240V 50/60Hz  
SELV: Si

## Source

Light source: LED  
Source power: 120W  
Source luminous flux: 18440lm  
Colour temperature: 4000K  
CRI: >80  
Colour tolerance: 3 Step MacAdam  
LED lifespan: 50000h L80 B20

## Compliance

CEI EN 60598-1:2015 + A11:2009. IEC 60598-2:2015 2-1

## Standards

Photobiological risk: RISK GROUP 0 Certified fixture in EXEMPT GROUP, in accordance with CEI EN 62471:2010-01, IEC TR 62778:2014.  
CAM edilizia: The product complies with the requirements for public buildings, ministerial decree of 23rd June 2022 n.256.

[LUCKY EVO B: View more product info](#)



Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy  
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com  
Company subject to the management and coordination by SLV GmbH

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.  
Last update: 6/8/2025, 13:11:23

# LUCKY EVO B

1002D9.02 + 1002A3.99

LUCKY EVO B: HF D/I 120W L2811 4KNE PUSH + LUCKY EVO B: DIFF. OPALE PER L2811

**novalux**  
ITALIAN LIGHTING DESIGN SINCE 1948



## Features

Use: Indoor  
Optics: OPAL  
Emergency: NO  
L: 2811mm  
A: 48mm  
H: 10mm  
Made in: ITALY  
Warranty: 5 years  
Weight: 0.5kg

## Tech data

IP: 40



Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy  
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com  
Company subject to the management and coordination by SLV GmbH

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.  
Last update: 6/8/2025, 13:11:23

# LUCKY EVO B

1002D9.02 + 1002A3.99

LUCKY EVO B: HF D/I 120W L2811 4KNE PUSH + LUCKY EVO B: DIFF. OPALE PER L2811

**novalux**  
ITALIAN LIGHTING DESIGN SINCE 1948

## COMPLETION ACCESSORIES

	LUCKY EVO B: MODULO CIECO L=1125 NERO	100261.02
	LUCKY EVO B: MODULO CIECO L=1406 NERO	100262.02
	LUCKY EVO B: MODULO CIECO L=1687 NERO	100263.02
	LUCKY EVO B: MODULO CIECO ANG. L=592 NE	100264.02
	LUCKY EVO B: COPPIA TESTATE CHIUSURA NER	100247.02
	LUCKY EVO B: KIT GIUNZIONE MODULI	100248.01

## MOUNTING ACCESSORIES

	KIT ALIMENTAZIONE L1200 3P NE	108919.02
	KIT ALIMENTAZIONE L3000 3P NE	108920.02
	KIT ALIMENTAZIONE L1200 5P NE	108921.02
	KIT ALIMENTAZIONE L3000 5P NE	108922.02



Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy  
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com  
Company subject to the management and coordination by SLV GmbH

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.  
Last update: 6/8/2025, 13:11:23

# LUCKY EVO B

1002D9.02 + 1002A3.99

LUCKY EVO B: HF D/I 120W L2811 4KNE PUSH + LUCKY EVO B: DIFF. OPALE PER L2811

**novalux**  
ITALIAN LIGHTING DESIGN SINCE 1948



LUCKY EVO B: KIT COPPIA CAVI SOSP. 5 M

**1002B5.99**



Novalux S.r.l. via Marzabotto, 2 40050 Funo di Argelato (BO) Italy  
Tel: +39 051 860558 · Fax +39 051 6647859 · Mail: info@novalux.it · VAT number 00536541204 · novalux.com  
Company subject to the management and coordination by SLV GmbH

This technical data sheet is owned by Novalux S.r.l., all rights reserved. Novalux S.r.l. reserves the right to make changes without prior notice.  
Last update: 6/8/2025, 13:11:23